



Compact, Dual-Frequency GNSS Receiver Delivers Robust RTK Functionality

Benefits

Proven NovAtel technology

Easy to integrate

Low power consumption

API reduces hardware requirements and system complexity

Features

Increased satellite availability with GLONASS tracking

L1, L2 and L2C signal tracking

GL1DE® smoothing algorithm

RT-2™, ALIGN® and RAIM firmware options

SPAN® INS functionality

High Precision GNSS, Compact Size

The dual-frequency OEM615 offers future ready, precise positioning for space constrained applications. Backward compatible with NovAtel's popular OEMV-1 form factor, the OEM615 provides the most efficient way to bring powerful Global Navigation Satellite System (GNSS) capable products to market quickly.

Designed with Performance and the Future In Mind

The OEM615 tracks all current and upcoming GNSS constellations and satellite signals including GPS, GLONASS, Galileo, BeiDou, and QZSS. It features configurable channels to optimize satellite availability in any condition, no matter how challenging. The OEM615 is software upgradable to track future signals as they become available. Maximizing satellite availability and optimizing GNSS signal usage now, and in the future, ensures consistent, high performance GNSS positioning.

Designed for Flexibility

The modular nature of NovAtel's OEM6® firmware gives users the flexibility to configure the OEM615 for their unique application needs. The OEM615 is scalable to offer sub-metre to centimetre level positioning, and is field upgradable to all OEM6 family software options. Options include AdVance® RTK for centimetre level real-time positioning, ALIGN® for precise heading and relative positioning, GL1DE® for decimetre level pass-to-pass accuracy and RAIM for increased GNSS pseudorange integrity.

Customization with an API

Application Programming Interface (API) functionality is available on the OEM615. Using a recommended compiler with the API library, an application can be developed in a standard C/C++ environment to run directly on the receiver platform, eliminating system hardware, reducing development time and resulting in a faster time to market.

If you require more information about our receivers, visit novatel.com/products/gnss-receivers/oem-receiver-boards



novatel.com

sales@novatel.com

1-800-NOVATEL (U.S. and Canada)

or 403-295-4900

China 0086-21-54452990-8011

Europe 44-1993-848-736

SE Asia and Australia 61-400-883-601

Performance¹

Channel Configuration

120 Channels ²	
Signal Tracking	
GPS	L1, L2, L2C
GLONASS	L1, L2
BeiDou ³	B1
Galileo	E1
SBAS	
QZSS	

Horizontal Position Accuracy (RMS)

Single Point L1	1.5 m
Single Point L1/L2	1.2 m
SBAS ⁴	0.6 m
DGPS	0.4 m
RT-2	1 cm + 1 ppm
Initialization time	< 10 s
Initialization reliability	> 99.9%

Measurement Precision (RMS)

Fully independent code and carrier measurements:		
	GPS	GLO
L1 C/A Code	4 cm	8 cm
L1 Carrier Phase	0.5 mm	1 mm
L2 P(Y) Code ⁵	8 cm	8 cm
L2 Carrier Phase ⁵	1 mm	1 mm
L2C Code ⁵	8 cm	8 cm
L2C Carrier Phase ⁶	0.5 mm	0.5 mm

Data Rate⁷

Measurements	up to 50 Hz
Position	up to 50 Hz

Time to First Fix

Cold Start ⁸	< 50 s
Hot Start ⁹	< 35 s

Signal Reacquisition

L1 < 0.5 s (typical)
L2 < 1.0 s (typical)

Time Accuracy¹⁹	20 ns RMS
-----------------------------------	-----------

Velocity Accuracy	0.03 m/s RMS
--------------------------	--------------

Velocity Limit¹¹	515 m/s
------------------------------------	---------

Physical and Electrical

Dimensions	46 x 71 x 11 mm
-------------------	-----------------

Weight	<24 g
---------------	-------

Power

Input Voltage	+3.3 VDC [±5%]
Power Consumption ¹²	<1.0 W, GPS L1/L2 1.1 W, GPS/GLONASS L1/L2 1.2 W, all on

Antenna LNA Power Output

Output Voltage	5.0 VDC
Maximum Current	100 mA

Connectors

Main	20-pin dual row male header
Antenna Input	MCX female

Communication Ports

3 LVTTTL	up to 921,600 bps
2 CAN Bus ¹³	1 Mbps
1 USB	12 Mbps
Pulse Per Second (PPS) output	

Environmental

Temperature

Operating	-40°C to +85°C
Storage	-55°C to +95°C

Humidity	95% non-condensing
-----------------	--------------------

Vibration

Random Vibe	MIL-STD 810G (Cat 24, 7.7 g RMS)
Sine Vibe	IEC 60068-2-6

Bump	ISO 9022-31-06 (25 g)
-------------	-----------------------

Shock	MIL-STD-810G (40 g)
--------------	---------------------

Features

- Field upgradeable software
- Multi-path mitigating technology
- Differential GPS positioning
- Differential correction support for RTCM 2.1, 2.3, 3.0, 3.1, CMR, CMR+ and RTCA
- Navigation output support for NMEA-0183 and detailed NovAtel ASCII and binary logs
- Auxiliary strobe signals, including a configurable output for time synchronization and mark inputs
- Outputs to drive external LEDs
- GL1DE smoothing algorithm

NovAtel Connect™

NovAtel Connect is an intuitive configuration and visualization tool suite allowing comprehensive control of the OEM615 product.

- Easy to use wizards guide you through positioning mode configuration and raw data collection
- Detailed graphical windows display comprehensive status information
- Plan view and playback files allow you to monitor the positioning and configuration history
- Remotely control and monitor the OEM615 over the internet
- Available on Windows XP, Windows 7 and Linux platforms

Firmware Options

- RT-2
- ALIGN
- RAIM
- SPAN

Optional Accessories

- GPS-700 series antennas
- ANT series antennas
- RF Cables—5 and 10 m lengths
- OEM6 Development Kit

High Vibration Hardware

The OEM615 is available as a High Vibration TCXO hardware variant, the OEM615V. This is compliant with MIL-STD810G (Category 24, 20 g RMS).



Version 3 - Specifications subject to change without notice

© 2013 NovAtel Inc. All rights reserved.

NovAtel, OEMV, Advant, GL1DE, OEM6 and ALIGN are registered trademarks of NovAtel Inc.

RT-2, OEM615 and NovAtel Connect are trademarks of NovAtel Inc.

Printed in Canada. D16170

OEM615 April 2013

For the most recent details of this product:

novatel.com/assets/Documents/Papers/OEM615.pdf

¹ Typical values. Performance specifications subject to GPS system characteristics, US DOD operational degradation, ionospheric and tropospheric conditions, satellite geometry, baseline length, multipath effects and the presence of intentional or unintentional interference sources.

² Tracks up to 60 L1/L2 satellites.

³ Designed for Compass Phase 3 B1 compatibility.

⁴ GPS only.

⁵ L2 P for GLONASS.

⁶ L2 C/A for GLONASS.

⁷ 50 Hz while tracking up to 20 satellites.

⁸ Typical value. No almanac or ephemerides and no approximate position or time.

⁹ Typical value. Almanac and recent ephemerides saved and approximate position and time entered.

¹⁰ Time accuracy does not include biases due to RF or antenna delay.

¹¹ Export licensing restricts operation to a maximum of 515 metres per second.

¹² Typical power consumption values.

¹³ User application software required.

